



### Features

- -40°C to +85°C operating temperature range
- 10/100 Ethernet, Gigabit Ethernet, 3D Video
- 4x Serial, 2x USB, 8x GPIOs
- PC/104 Expansion
- Ultra Low Power
- 486 migration

### Specifications

#### Core System

CPU	300MHz Vortex86SX or 800MHz Vortex86DX
Cache	16kB I-cache, 16kB D-cache
Memory	256MB soldered DDR2
System Controllers	PC-compatible DMA and interrupt controller and timers
Real Time Clock	Battery-backed RTC/CMOS
Powerfail Reset	Triggers when key voltage drops below predetermined thresholds
BIOS	AMI BIOS

#### Bus Interface

PC/104	ISA
--------	-----

#### Multi I/O and Storage

PATA	DMA 100 IDE interface supports up to two hard drives
Storage	CompactFlash socket
Serial	2x RS-232, 2x RS-232/422/485
USB	2x USB 2.0 ports
KB/MS	PS/2 interface
GPIO	Eight general-purpose digital I/O pins

#### Ethernet

Ethernet	1x integrated Vortex86 10/100 port and 1x Intel 82451PI Gigabit Ethernet
----------	--

#### Video

Graphics Engine	Integrated 2D, 64-bit, single-cycle, 100MHz
Resolution	1600x768
Video Memory	32MB/64MB DDR2
VGA	Yes
TTL/TFT	Dual channels 12-bit or Single Channel 18-bit color depths Supports 3.3V, 5V flat panels

#### Power

Power Requirement	1.3A @5V
-------------------	----------

#### Mechanical and Environmental

Form Factor	PC/104
Dimensions	90x96mm (3.6x3.8")
Board Thickness	0.093" (2.36mm thick)
Operating Temperature	(100 LFM system air flow) • Standard: -20°C to +70°C • Extended: -40°C to +85°C
Storage Temperature	-55°C to +85°C

#### Operating Systems

Extended Support (BSP) Win XPe, WinCE 5.0/6.0, QNX 6.5

### Ordering Information

#### Modules

Model Number	Description/Configuration
CM-435-R-10	CoreModule® 435, 300MHz Vortex CPU, 256MB RAM, Video, 10/100 & Gigabit Ethernet
CM-435-R-12	CoreModule® 435, 800MHz Vortex CPU, 256MB RAM, Video, 10/100 & Gigabit Ethernet

#### Accessories

Model Number	Description/Configuration
CM-435-L-10	300MHz QuickStart Kit (CM-435-R-10 SBC, cable kit, software, documentation)
CM-435-L-12	800MHz QuickStart Kit (CM-435-R-12 SBC, cable kit, software, documentation)